


SM-51.2V(48V)300AH





Su-mak lithium batteries are widely used in industrial, residential, commercial and private applications. The maintenance free construction and advanced design features makes the lithium series the definitive choice for a wide variety of markets. Like solar and renewable energy storage, electric vehicle, golf cart and industrial equipment, floor machines, forklifts, aerial lifts, and robotics; marine. RV, and no-idle solution; Mobility and Medical Equipment; Telecom, Broadband and Cable TV; UPS systems.

Applications

































BATTERY SPECIFICATIONS

Battery type-Chemistry	LiFePO4	Voltage Window	43.2V-58.4V
Nominal Voltage	51.2V	Recommend Charge Voltage	57.6V
Nominal Capacity	300Ah	Max Charge Voltage	58.4V
Energy Density	15360Wh	Recommend Charge Current	20A
Dimensions(LxWxH)	825*413*233mm	Max Continuous Current	150A
Weight	120KGS	Recommend Discharge Voltage	44.8V
Terminal Type	Plug-in	Max Discharging Voltage	43.2V
Terminal Torque	8.5NM	Max Continuous Discharge Current	150A
Case Material	SPCC	Peak Discharge Current	200A
BMS build-in	Yes	Cycle Life(0.2C, 25°C@80% DOD)	6000 Cycles
AH Efficiency – round trip	>98%	Discharge Temperature	(- 20 to 55)°C
Self Discharge per Month	<3%	Charge Temperature	(0 to 55)°C
Max in Parallel	16PCS	Storage Temperature	(- 20 to 45)°C
Max in Series	Not Allowed	Bluetooth(App)	Optional
LCD Screen	Optional	Heating Function	Optional

BMS CHARACTERISTICS

Primary Charging Protection	Current :155A	Delay Time: 20s
Second Charging Protection	Current :160A	Delay Time: 2~3s
Primary Discharging Protection	Current :155A	Delay Time: 10s
Second Discharging Protection	Current :200A	Delay Time: 100ms
Over charge Voltage Protection	Voltage :58.4V	Delay Time: 1~2s
Over Discharge Voltage Protection	Voltage :43.2V	Delay Time: 1~2s
Temperature Protection	PCB Temperature≥95	°C


Recover≤85


Communication Port Major RS485, optional for CAN / Dry port, customized acceptable





Discharge Time	1h	2h	3h	4h	5h	10h	20h
Cut off voltage (44.8V)		150A	100A	75A	60A	30A	15A

Discharge Time	1h	2h	3h	4h	5h	10h	20h
Cut off voltage (44.8V)		7680W	5120W	3840W	3072W	1536W	768W









Note 1: Please always refer to the latest edition of our technical manual that published on our website to ensure safe and efficient operation.

Note 2: When make parallel connection, please full discharge batteries, then recharge after parallel connected; when series connect, please keep batteries with same remain capacity/

Note 3: Parallel connection is only for longer backup time, not for larger output power.